

Eng



VIVAX VOX

VIVAX Model : SP-7080H

Ean code 3856005182343



DESCRIPTION	
Bluetooth/ HDMI ARC Sound Bar Speaker, USB player; MP3/WMA/FLAC,WAV,APE USB Play; HDMI ARC / RCA Coax Audio IN / Optical Audio IN / AUX 3,5mm IN / USB; 70W RMS Audio output (13,4cm Bass speaker + 2x5,1cm Mid/Twitter speaker), White LCD Display, Full Remote Controller, EQ 3 Modes + 3D Surround Effect	
SPECIFICATIONS	
PLL FM Radio	-
AM Radio	-
Auto Radio search & Store	-
Programme memories	-
CD	-
Remote controler	Yes (20 buttons), full function
LCD Display	Yes (Mode / Input / Vol)
BBS (Bass boost sound)	-
Equalizer function	Yes, (Music (EQ1), Film (EQ2), News (EQ3)
Clock	-
Auto ON/OFF	-
Amplifier	2.1Ch, 2x15W + 1x40W RMS
Frequency range	40Hz-200Hz Subwoofer + 200Hz-16kHz Main Unit, +/- 3dB, S/N:>70dB, Distortion: <0,1% 1kHz,1W
MULTIMEDIA	
MP3/WMA/FLAC/WAV/AAC	Yes / Yes / Yes / Yes / -
Other	Full Function Remote Controller, Bluetooth 5.1, White 4 digit LCD Display, 4xSide Buttons (Power On/Off, Mode, Vol+/-), 2m RCA cable for Subwoofer connection



TERMINALS	
AUX-IN / AUX Out	Yes, 3,5mm / -
DIGITAL Coax / Optical	Yes / Yes
HDMI	Yes, ARC
USB	Yes / MP3/WMA/FLAC,WAV,APE Play
SW OUT (Subwoofer connection)	RCA
SD/MMC	-
DC IN connection	Yes
POWER / DIMENSIONS	
Audio Power	70W RMS
Speakers	1x Bass 40W / 13,4cm 2x15W Mid / Twitter 5,1cm
W x H x D unit dimension	800 x 65 x 60 (main unit) 220 x 190 x 270 mm (Subwoofer)
W x H x D box dimension	845 x 246 x 352 mm
Weight Gross/Net	5,0 / 3,8kg
Power	100-240V, 50/60Hz / 19V, 2,5A
ACCESSORIES	
Instruction manual	English, Croatian, Serbian, Macedonian, Albanian, Slovenian + local market languages
Remote controller	Yes, 20 buttons
Other	1xAdapter, Wall hang screws set, 3,5mm Aux cable

* Due to different formats and codec format version, it is possible that all specified formats will not be supported. The manufacturer is not responsible for a such problems and it is not considered a malfunction of the device.

* Product specifications are subject to change without notice.